


MDC-3ZW Z-Wave Mini Door / Window Contact

Ideal Choice to Guard
Your Doors and Windows



- Discreet & slim design
- Built-in reed switch
- Wireless flexible installation

The MDC-3ZW is a discreet miniature door sensor that monitors the irregular opening / closing of doors and windows. The MDC-3ZW is particularly small, which allows for highly flexible and virtually invisible installation.

Integrating the MDC-3ZW into a security or home automation system will allow users to create scenes and automatically control lights and electronic appliances when doors or windows open and close. The MDC-3ZW features a pre-inserted battery with minimal power consumption, and transmits supervisory and low battery signals to check system integrity.

As a Z-Wave device, the MDC-3ZW can be flexibly integrated into new or existing Z-Wave systems.

Features

- Monitors the opening / closure of doors and windows
- Discreet, small, sleek design to be mounted on door or window frames (self-adhesive or screw mounting)
- Enables security and home automation systems scene creation to turn on/off appliances accordingly
- Minimum power consumption
- Tamper protection to prevent unauthorized removal
- Built-in reed switch
- LED status indicator
- Supervisory signals to ensure optimal operation
- Low battery detection
- Suitable for residential and commercial security
- Compatible with other manufacturers' Z-Wave systems

Specifications

Communication Protocol	Z-Wave Plus 500 series module
Frequency	868.40 MHz (EU) / 908.40 MHz (US)
Power Source	3V, CR2450 Lithium battery x 1
Battery Life	2.3 years*
Operating Temperature	-10°C to 45°C (14°F to 113°F)
Operating Humidity	Up to 85% non-condensing
Dimensions	58mm x 28mm x 10mm (body) 25mm x 15mm x 7.35mm (magnet)
Weight	15g (body); 7g (magnet)

* Note: Actual battery life may vary with product settings, operating environment and usage.